

Byron™ DB333 Wire Free Chime Kit **75Metres**

1

Using a small flat screwdriver, insert into the locking clip and gently twist. The back plate will undip from the Bell Push.

2

Insert the 23A battery (Supplied) into the battery holder, making sure the Positive/Negative terminals match the internal markings.

3

Insert the Plug-through Chime into a standard 220-240V ~50Hz wall socket and switch the socket ON.

4

Plug in a standard plug e.g. Table light.
Max load: 1000W

Bell Push & Door Chime:

- 1: Using back plate as template.
- 2: Making sure UP arrow points UP.
- 2: Mark and drill holes.
- 3: Insert wall plugs and attach to wall using screws provided.
- 4: Clip the Bell Push on to the back plate making sure Bell Push 'Clicks' in to place.
- 5: Plug the Door Chime into a socket, within the operating range (75M). Transmission of the wire free signal through Walls, Doors and Ceilings etc, may reduce the operating range. Chime is designed for INDOOR use only.

Melody Selection:

To select a new melody for the Door Chime

- 1: Press the Melody Select button on the front of the chime.
- 2: The chime will play the newly selected sound.
- 3: Press again to select the next melody.

Installation Guide:

Avoid positioning the Bell Push/Chime on or directly near metallic surfaces as this may reduce the operation range.
UPVC Door Frames:
When positioning the bell push onto a UPVC door, always check the operating performance before final installation, internal metal frame of the door may affect performance.

Tip: Try adjusting the location of the Bell Push slightly to the Left/Right or place on external wall.

Replacement and Additional Chimes/Bell Pushes:
The Byron DB door chime kit is preset to work together. For additional or replacement chimes and pushes please contact the 'Byron Help Line' for availability

Specification
Bell Push: DBT
Power: 1 x 23A 12V DC Battery (supplied)
IP44 Weather Resistant

Plug-Through Door Chime: DB303
Power: 220-240V ~50Hz
Range: 75 Metres
Max Load: 1000W
Indoor Use Only



Tel: 0845 2301231 (UK)
9-5 Mon-Fri, Local call charges apply
support@chbyron.com
www.chbyron.com

GB: CH Byron
Byron House, Sherwood Rd
Astonfields, Bromsgrove
B60 3DR
UK

http://www.

Byron 433.92MHz

R&TTE APPROVED

A	B	DK	FIN	F	GB	LT	IRL	L	NL	P	S	UK	BG	CZ	EST	H	IS	LV	M	N	SK	SLO	CH	PL	RO
---	---	----	-----	---	----	----	-----	---	----	---	---	----	----	----	-----	---	----	----	---	---	----	-----	----	----	----

CH Byron Electrical United Kingdom. www.chbyron.com

Project Manager
Mr G Hunter

SN: SP020910